

August 3, 2026

Patrick Doherty, Program Manager
Performance Assessment Division
Office of Energy Infrastructure Safety
California Natural Resources Agency
715 P Street 20th Floor
Sacramento, CA 95814

BY ENERGY SAFETY E-FILING

SUBJECT: Southern California Edison Company's Response to Notice of Non-Performance (NON_PAD_SCE_YLO_20260616_1319)

Dear Mr. Doherty:

Southern California Edison Company (SCE) appreciates the opportunity to provide this response to the finding identified in the Notice of Non-Performance – **NON_PAD_SCE_YLO_20260616_1319** which SCE received on **July 2, 2026 (Notice)**, based on the Office of Energy Infrastructure Safety's (Energy Safety) field inspections conducted in SCE's service area on **June 16, 2026**. SCE appreciates Energy Safety's efforts to identify, communicate and work together to resolve potential wildfire risks.

If you have any questions, or require additional information, please contact Liz Leano at 626-302-3662 or Elizabeth.Leano@sce.com.

Sincerely,

//s//

Brandon Tolentino
Vice President of Wildfire and Business Resiliency
Southern California Edison

SCE Response

Finding:

Notice	#	Structures
NON_PAD_SCE_YLO_20260616_1319	1	5037269E

Summary of Findings:

On June 16, 2026, Energy Safety conducted an inspection of Southern California Edison Company's WMP initiatives in the vicinity of the city of Corona, California. The inspection report is enclosed herewith. Energy Safety found the following deficiencies: Deficiency 1. Energy Safety observed that in implementing 2025 WMP initiative 8.1.2.1.1 – Covered Conductor, SCE failed to complete work on covered conductor on Structure ID 5037269E, Grid Hardening ID TD2244140-5037269E at coordinates 33.849071999277, -117.52490100003.

Energy Safety states that it “considers this non-performance to be in the Minor risk category.”¹

Response:

The Notice states that “a dislodged lightning arrester cover was observed at the inspection location.” SCE confirms that the lightning arrester cover on structure 5037269E was installed and in place as of November 21, 2025, as part of the subject covered conductor installation. During a subsequent inspection in response to this Notice, SCE's Field Operations team identified that the previously installed lightning arrester cover had become dislodged, likely due to environmental exposure or other external factors. On July 27, 2026, SCE field personnel remediated the lightning arrester cover on structure 5037269E. Please see the photo below showing the completed lightning arrester cover remediation.

¹ Notice, p. 1.

